

| Rozdělení                     | Typ oscilátoru                               | Jmenovitý kmitočet [MHz] | Nap. napětí / Odběr proudu [V]/[mA] | Stabilita kmitočtu* [ppm] | Výstupní signál | Dostavení M-mech. V-napětím R-rezist. |     |
|-------------------------------|--|--------------------------|-------------------------------------|---------------------------|-----------------|---------------------------------------|-----|
| OCXO                          | OCXO10                                       | <a href="#">HC 3410</a>  | 3 - 25                              | 12/100                    | ±0,3            | sin                                   | V   |
|                               |  | <a href="#">HC 3414</a>  | 3 - 25                              | 12/100                    | ±0,2            | HCMOS                                 | R   |
|                               |  | <a href="#">HC 3415</a>  | 3 - 25                              | 12/100                    | ±0,2            | HCMOS                                 | R   |
|                               |  | <a href="#">HC 3416</a>  | 3 - 25                              | 12/100                    | ±0,2            | sin                                   | R   |
|                               |  | <a href="#">HC 3417</a>  | 5 - 40                              | 12/110                    | ±0,05           | sin                                   | R/V |
|                               |  | <a href="#">HC 3418</a>  | 5 - 40                              | 12/110                    | ±0,05           | ACMOS                                 | R/V |
|                               | OCXO12                                       | <a href="#">HC 3412</a>  | 5 - 25                              | 5/50                      | ±0,5            | sin                                   | V   |
| TCXO                          | TCXO6  | <a href="#">HC 3306</a>  | 4 - 40                              | 5/3                       | ±2,5            | sin                                   | V,M |
|                               |  | <a href="#">HC 3307</a>  | 4 - 40                              | 5/3                       | ±2,5            | sin                                   | M   |
|                               |  | <a href="#">HC 3321</a>  | 4 - 40                              | 5/15                      | ±2,5            | HCMOS                                 | V,M |
|                               |  | <a href="#">HC 3322</a>  | 4 - 40                              | 5/15                      | ±2,5            | HCMOS                                 | M   |
|                               |  | <a href="#">HC 3323</a>  | 4 - 40                              | 3,3/10                    | ±2,5            | HCMOS                                 | V,M |
|                               |  | <a href="#">HC 3324</a>  | 4 - 40                              | 3,3/10                    | ±2,5            | HCMOS                                 | M   |
| CXO                           | CXO  | <a href="#">HC 3631</a>  | 4 - 80                              | 5/50                      | ±1000           | TTL                                   | -   |
|                               |  | <a href="#">HC 3632</a>  | 4 - 80                              | 5/50                      | ±100            | TTL                                   | -   |
|                               |  | <a href="#">HC 3633</a>  | 4 - 80                              | 5/50                      | ±1000           | TTL                                   | -   |
|                               |  | <a href="#">HC 3634</a>  | 4 - 80                              | 5/50                      | ±100            | TTL                                   | -   |
|                               |  | <a href="#">HC 3635</a>  | 4 - 80                              | 5/50                      | ±80             | TTL                                   | -   |
|                               |  | <a href="#">HC 3636</a>  | 4 - 80                              | 5/50                      | ±1000           | TTL                                   | -   |
|                               |  | <a href="#">HC 3637</a>  | 4 - 80                              | 5/50                      | ±100            | TTL                                   | -   |
|                               |  | <a href="#">HC 3638</a>  | 4 - 80                              | 5/50                      | ±50             | TTL                                   | -   |
|                               |  | <a href="#">HC 3639</a>  | 4 - 80                              | 5/50                      | ±80             | TTL                                   | -   |
| VCXO                          | VCTCXO6                                      | <a href="#">HC 3104</a>  | 4 - 30                              | 5/3                       | ±2,5            | sin                                   | V,M |
| <a href="#">Váš oscilátor</a> | Oscilátor s parametry podle vašeho požadavku |                          |                                     |                           |                 |                                       |     |